

```
01 LBL "DT" ;PPC ROM Display Test
02 "\F8\00\00\10\00\21\E8" ;F80000100021E8 hex = Anunciators on
03 RCL M
04 " , , , , , , " ;6 commas
05 ASTO L
06 ARCL L
07 AON
08 PSE
09 AOFF
10 "\80\3A\80\3A\80\3A" ;803A803A803A = (boxed star, colon) 3 times
11 ASTO L
12 ARCL L
13 ARCL L
14 ARCL L
15 AVIEW
16 X<> d
17 STOP
18 X<> d
19 RDN
20 CLD
21 RTN
22 LBL "AD" ;PPC ROM Alpha Delete Last Character
23 RCL P
24 RCL O
25 .
26 X<> N
27 ">*****" ;Append 6 asterisks
28 RCL N
29 CLA
30 STO M
31 ASTO X
32 RDN
33 STO M
34 RDN
35 STO N
36 RDN
37 STO O
38 .1
39 STO P
40 ASHF
41 ARCL Z
42 END
```

```
0065C000F3004454F7F80000100021E89075F62C2C2C2C2C
9A749B748C898BF6803A803A803A9A749B749B749B747ECE7E
84CE7E757F85C000F3004144907890771ACE76F77F2A2A2A2A
2A2A90768791759A737591757591767591771A119178889B71
C0000DAA
```

101 BYTES

# HP-41C PPC ROM Synthetic Group 6 by Various Authors V7 N10 P17 Dec 1980

Program Registers Needed: 15

Row 1 (1 - 2)




Row 2 (2 - 6)



Row 3 (6 - 11)



Row 4 (12 - 19)



Row 5 (20 - 25)



Row 6 (26 - 29)



Row 7 (30 - 37)



Row 8 (38 - 42)

