

```
01 LBL "XE"      ;PPC ROM XROM Entry Routine
02 XEQ 14
03 LBL 14
04 >"**"        ;Append 2 asterisks
05 STO N
06 RDN
07 SF 14
08 RCL b
09 X<> N
10 FC? 14
11 CLA
12 FC?C 14
13 RTN
14 >"***"       ;Append 3 asterisks
15 X<> M
16 X<> N
17 X<> M
18 >"**"        ;Append 2 asterisks
19 STO N
20 X<> O
21 X<> N
22 >"**"        ;Append 2 asterisks
23 X<> N
24 STO b
25 LBL "HD"      ;PPC ROM Hide Data Registers
26 SIGN
27 RDN
28 RCL c
29 "\10"        ;10 hex = Theta
30 X<> M
31 >"**"        ;Append 2 asterisks
32 STO N
33 RDN
34 ASTO IND L
35 SREG IND L   ;SigmaReg
36 LBL "~C"     ;~=Sigma PPC ROM Sigma Register Curtain Exchange
37 CLA
38 RCL c
39 STO O
40 STO M
41 >"A"
42 CLX
43 STO N
44 >"B"
45 STO M
46 >"CD"
47 X<> O
48 X<> d
49 SF 08
50 X<> d
51 X<> N
52 >"E"
53 X<> d
54 SCI IND N
55 X<> d
56 STO O
57 RDN
58 RCL c
59 SREG 00      ;SigmaREG
60 X<> c
61 STO M
62 >"F"
63 RDN
64 RCL N
65 >"GHI"
66 STO L
67 RDN
```

```

68 RCL c
69 STO M
70 X<> O
71 >"J"
72 STO M
73 >"K"
74 X<> L
75 STO M
76 >"L"
77 X<> N
78 X<> c
79 RDN
80 CLA
81 END

```

```

00B9C000F3005845E0000E0FF37F2A2A917675A80E907CCE76
AD0E87AB0E85F47F2A2A2ACE75CE76CE75F37F2A2A9176CE77
CE76F37F2A2ACE76917CC000F30048447A75907DF110CE75F3
7F2A2A9176759AF499F4C000F3007E4387907D91779175F27F
41779176F27F429175F37F4344CE77CE7EA808CE7ECE76F27F
45CE7E9DF6CE7E917775907D9900CE7D9175F27F46759076F4
7F474849917475907D9175CE77F27F4A9175F27F4BCE749175
F27F4CCE76CE7D7587C0000D19

```

185 BYTES

HP-41C PPC ROM Page Switch 2 by PPC ROM Authors
 PPC Calculator Journal V8 N1 Pg 27 Jan-Feb 1981

```

01 LBL "IP"      ;PPC ROM Initialize Page
02 XEQ 14
03 R^
04 X<> c
05 RDN
06 RTN
07 LBL "PS"      ;PPC ROM Page Switch
08 E3
09 /
10 +
11 ASTO Y
12 XEQ 14
13 FRC
14 E3
15 ST* Y
16 RDN
17 RCL d
18 FIX 0
19 CF 29
20 " "           ;1 space
21 ARCL L
22 >" OFF;"
23 ARCL Y
24 >" ON"
25 STO d
26 X<> L
27 INT
28 FC? 10
29 PROMPT
30 FC? 10
31 GTO 13
32 FS? 24
33 RTN
34 XEQ "TN"      ;PPC ROM Tone N (PPC ROM Page Switch 3 TN Line 1)
35 XEQ "TN"      ;PPC ROM Tone N (PPC ROM Page Switch 3 TN Line 1)
36 R^
37 R^
38 LBL 13
39 240
40 RDN
41 CLX

```

```

42 X<> IND T
43 STO c
44 XEQ IND Z
45 XEQ "GE" ;PPC ROM Go to .END. (PPC ROM Page Switch 5 14 Line 16)
46 LBL 14
47 XEQ "E?" ;PC ROM END Finder (PPC ROM Page Switch 5 14 Line 53)
48 257
49 -
50 X<0?
51 GTO 14
52 R^
53 SIGN
54 R^
55 R^
56 SREG T ;SigmaREG
57 XEQ "OM" ;PPC ROM Open Memory (PPC ROM Page Switch 5 14 Line 6)
58 STO M
59 240
60 ASTO IND X
61 R^
62 R^
63 RTN
64 LBL 14
65 ENTER
66 XEQ "S?" ;PPC ROM Size Finder (PPC ROM Page Switch 4 S? Line 1)
67 +
68 "OVERSIZE"
69 XEQ "VA" ;PPC ROM View Alpha (PPC ROM Page Switch 3 TN Line 11)
70 XEQ "GE" ;PPC ROM Go to .END. (PPC ROM Page Switch 5 14 Line 16)
71 END

```

```

009FC000F3004950E0000E74CE7D7585C000F30050531B1343
409A72E0000E691B13947275907E9C00A91DF1209B74F67F20
4F46463B9B72F47F204F4E917ECE7468AD0A8EAD0ABE00AC18
851EF2544E1EF2544E74740E1214107577CEF0917DAEF11EF2
47450F1EF2453F1215174166BF00747A747499701EF24F4D91
751214109AF37474850F831EF2533F40F84F56455253495A45
1EF256411EF24745C0000D57

```

159 BYTES

HP-41C PPC ROM Page Switch 3 by PPC ROM Authors
 PPC Calculator Journal V8 N1 Pg 27 Jan-Feb 1981

```

01 LBL "TN" ;PPC ROM Tone N
02 "\9F" ;9F hex
03 XEQ "DC" ;PPC ROM Decimal to Char (Line 20)
04 >"\85" ;Append 85 hex
05 ASTO T
06 SF 25
07 "\06\00" ;0600 hex
08 XEQ "XE" ;PPC ROM XROM Entry (PPC ROM Page Switch 1 XE Line 1)
09 CF 25
10 RTN
11 LBL "VA" ;PPC ROM View Alpha
12 SF 25
13 XROM 29,08 ;PRA
14 FS?C 21
15 CF 25
16 AVIEW
17 FC?C 25
18 SF 21
19 RTN
20 LBL "DC" ;PPC ROM Decimal to Character
21 INT
22 256
23 MOD
24 LASTX
25 +
26 OCT

```

```

27 X<> d
28 FS?C 11
29 SF 12
30 FS?C 10
31 SF 11
32 FS?C 09
33 SF 10
34 FS? 07
35 SF 09
36 FS? 06
37 SF 08
38 X<> d
39 X<> M
40 RCL N
41 >"*" ;Append 1 asterisk
42 X<> O
43 X<>Y
44 STO N
45 X<> P
46 >"*" ;Append 1 asterisk
47 STO P
48 RDN
49 X<> O
50 X<> N
51 STO M
52 RDN
53 END

```

```

0075C000F300544EF19F1EF24443F27F859A70A819F206001E
F25845A91985C000F3005641A819A748AA15A9197EAB19A815
85C000F3004443681215164B76406FCE7EAA0BA80CAA0AA80B
AA09A80AAC07A809AC06A808CE7ECE759076F27F2ACE777191
76CE78F27F2A917875CE77CE76917575C0000D50

```

117 BYTES

HP-41C PPC ROM Page Switch 4 by PPC ROM Authors
 PPC Calculator Journal V8 N1 Pg 27 Jan-Feb 1981

```

01 LBL "S?" ;PPC ROM Size Finder
02 XEQ "C?" ;PPC ROM Curtain Finder (Line 15)
03 CHS
04 LBL 13
05 64
06 MOD
07 SF 25
08 LBL 02
09 RCL IND X
10 FC? 25
11 RTN
12 X<> L
13 +
14 GTO 02
15 LBL "C?" ;PPC ROM Curtain Finder
16 RCL c
17 LBL 14
18 STO M
19 >"\00\00\41" ;Append 2 nulls, letter A
20 X<> M
21 X<> d
22 CF 01
23 CF 02
24 CF 04
25 CF 07
26 FS?C 10
27 SF 07
28 FS?C 11
29 SF 09
30 FS?C 12
31 SF 10

```

32 FS?C 13
33 SF 11
34 FS?C 14
35 SF 13
36 FS?C 15
37 SF 14
38 FS?C 16
39 SF 15
40 X<> d
41 E38
42 /
43 INT
44 DEC
45 RTN
46 END

0060C000F300533F1EF2433F540E16144BA8190390F3AD1985
CE7440B300C000F300433F907D0F9175F47F000041CE75CE7E
A901A902A904A907AA0AA807AA0BA809AA0CA80AAA0DA80BAA
0EA80DAA0FA80EAA10A80FCE7E1B131843685F85C0000DF7

96 BYTES

HP-41C PPC ROM Page Switch 5 by PPC ROM Authors
PPC Calculator Journal V8 N1 Pg 28 Jan-Feb 1981

01 LBL 14
02 16
03 -
04 SIGN
05 RDN
06 LBL "OM" ;PPC ROM Open Memory
07 XEQ 14
08 " \1F\F0\01\69\01" ;1FF0016901 hex
09 X<> M
10 STO N
11 >"*" ;Append 2 asterisks
12 X<> N
13 CLA
14 X<> c
15 RTN
16 LBL "GE" ;PPC ROM Go to .END.
17 SF 25
18 RCL b
19 CLA
20 FC?C 25
21 RTN
22 STO N
23 RDN
24 XEQ 14
25 X<> d
26 SF 05
27 SF 06
28 X<> d
29 STO M
30 CLX
31 X<> N
32 >"*" ;Append 2 asterisks
33 STO M
34 >"*" ;Append 2 asterisks
35 X<> N
36 CLA
37 X<> M
38 RDN
39 LBL "Ab" ;PPC ROM Alpha Store b
40 ASTO b
41 LBL 14
42 RCL c
43 STO M
44 >"\00\00\00\00\00" ;Append 5 nulls

```

45 X<> M
46 X<> d
47 CF 00
48 CF 01
49 CF 02
50 CF 03
51 X<> d
52 RTN
53 LBL "E?"      ;PPC ROM .END. Finder
54 RCL c
55 XEQ "2D"      ;PPC ROM Decode 2 Bytes to Decimal
56 16            ;(PPC ROM Page Switch 6 2D Line 1)
57 MOD
58 LASTX
59 X^2
60 *
61 RCL M
62 +
63 CLA
64 END

```

```

00900F1116417A75C000F3004F4DE0000EF51FF0016901CE75
9176F37F2A2ACE7687CE7D85C000F3004745A819907C87AB19
85917675E0000ECE7EA805A806CE7E917577CE76F37F2A2A91
75F37F2A2ACE7687CE7575C000F30041629A7C0F907D9175F6
7F0000000000CE75CE7EA900A901A902A903CE7E85C000F300
453F907D1EF2324411164B76514290754087C0000D47

```

144 BYTES

HP-41C PPC ROM Page Switch 6 by PPC ROM Authors
 PPC Calculator Journal V8 N1 Pg 28 Jan-Feb 1981

```

01 LBL "2D" ;PPC ROM Decode 2 bytes to Decimal
02 "*"
03 X<> M
04 X<> N
05 ASHF
06 >"\00\07\00\06\00\00" ;Append 000700600000 hex
07 X<> M
08 X<> N
09 X<> M
10 >"\00\00\05" ;Append 2 nulls, 05 hex
11 RCL M
12 INT
13 +
14 RCL N
15 *
16 ST+ M
17 X<> N
18 RCL O
19 INT
20 HMS
21 *
22 RCL O
23 +
24 E1
25 ST* M
26 *
27 X<> M
28 RTN
29 END

```

```

003EC000F3003244F12ACE75CE7688F77F000700600000CE75
CE76CE75F47F000005907568409076429275CE769077686C42
9077401B11947542CE7585C0000D60

```

62 BYTES


HP-41C ROM Page Switch 1 by Various Authors PPC V8 N1 P27 Jan-Feb 1981

Program Registers Needed: 27

Row 1 (1 - 4)



Row 2 (4 - 11)



Row 3 (12 - 17)



Row 4 (17 - 22)



Row 5 (22 - 26)



Row 6 (27 - 32)



Row 7 (33 - 38)



Row 8 (38 - 44)



Row 9 (44 - 49)



Row 10 (50 - 55)




Row 11 (56 - 62)



Row 12 (62 - 68)



Row 13 (68 - 73)



Row 14 (74 - 80)



Row 15 (81)



HP-41C ROM Page Switch 2 by Various Authors PPC V8 N1 P27 Jan-Feb 1981

Program Registers Needed: 23

Row 1 (1 - 5)




Row 2 (6 - 11)



Row 3 (12 - 18)



Row 4 (19 - 22)




Row 5 (23 - 28)



Row 6 (28 - 34)



Row 7 (35 - 42)



Row 8 (42 - 47)



Row 9 (47 - 56)



Row 10 (56 - 61)



Row 11 (62 - 68)



Row 12 (68 - 70)



Row 13 (71)



HP-41C ROM Page Switch 3 by Various Authors PPC V8 N1 P27 Jan-Feb 1981

Program Registers Needed: 17


Row 1 (1 - 4)



Row 2 (4 - 8)



Row 3 (9 - 13)



Row 4 (14 - 20)



Row 5 (20 - 27)



Row 6 (28 - 34)



Row 7 (34 - 40)



Row 8 (41 - 46)



Row 9 (47 - 53)



HP-41C ROM Page Switch 4 by Various Authors PPC V8 N1 P27 Jan-Feb 1981

Program Registers Needed: 14

Row 1 (1 - 5)



Row 2 (5 - 13)



Row 3 (14 - 18)



Row 4 (19 - 23)



HP-41C ROM Page Switch 4 by Various Authors PPC V8 N1 P27 Jan-Feb 1981


Row 5 (24 - 30)




Row 6 (30 - 36)



Row 7 (37 - 43)



Row 8 (44 - 46)



HP-41C ROM Page Switch 5 by Various Authors PPC V8 N1 P28 Jan-Feb 1981

Program Registers Needed: 21

Row 1 (1 - 7)



Row 2 (7 - 11)



Row 3 (11 - 16)



Row 4 (16 - 23)



Row 5 (24 - 29)



Row 6 (30 - 34)



Row 7 (35 - 40)



Row 8 (40 - 44)



Row 9 (45 - 51)



Row 10 (51 - 55)



HP-41C ROM Page Switch 5 by Various Authors PPC V8 N1 P28 Jan-Feb 1981

Row 11 (55 - 64)



Row 12 (64)



HP-41C ROM Page Switch 6 by Various Authors PPC V8 N1 P28 Jan-Feb 1981

Program Registers Needed: 9


Row 1 (1 - 5)



Row 2 (6 - 9)



Row 3 (9 - 15)



Row 4 (16 - 24)



Row 5 (24 - 29)

