

HP-41C X-Function/Memory Test by G. Richard Atwood  
PPC Calculator Journal Vol 9 No 3 Page 25 Apr 1982  
The program requires PPC ROM and X-Function/Memory

```
01 LBL "COW" ;Program in main memory tests EF/M
02 BEEP
03 RTN
04 LBL "TEST" ;XEQ "TEST" to test jump into EF/M
05 STO 01
06 "\02\BD" ;Address 2,189 = SB (Line 02)
07 XROM 10,19 ;XE - XROM Entry from PPC ROM
08 "\04\BB" ;Address 2,187 = SB (Line 10)
09 XROM 10,19 ;XE - XROM Entry from PPC ROM
10 END
```

001FC000F400434F578685C000F5005445535431F202BDA293  
F2040BA293C0000DD6

31 BYTES

HP-41C X-Function/Memory Sub. by G. Richard Atwood  
PPC Calculator Journal Vol 9 No 3 Page 25 Apr 1982  
The program requires PPC ROM and X-Function/Memory

```
01 LBL "SB" ;Place as first program in EF/M
02 XROM 10,47 ;T1 - Beep Alternative
03 LBL 01
04 RCL 01
05 VIEW X
06 XROM 10,32 ;TN - Tone N
07 DSE 01
08 GTO 01
09 RTN
10 "\08\B9" ;Address 8, 185 = SB Line 14
11 XROM 10,19 ;XE - XROM Entry from PPC ROM
12 "ABCD"
13 XROM 29,08 ;PRA - Print Alpha Marker ABCD
14 GTO "COW" ;COW - Calling Program (Line 1)
15 END
```

0027C000F3005342A2AF02219873A2A09701B20085F208B9A2  
93F441424344A7481DF3434F57C0000D9A

39 BYTES

# HP-41C EF/M Test Pgm. COW by G. Richard Atwood PPC V9 N3 P25 Apr 1982

Program Registers Needed: 5

Row 1 (1 - 4)



Row 2 (4 - 8)



Row 3 (9 - 10)




# HP-41C EF/M Subroutine SB by G. Richard Atwood PPC V9 N3 P25 Apr 1982

Program Registers Needed: 6

Row 1 (1 - 6)



Row 2 (6 - 12)



Row 3 (12 - 15)

