

## User instructions,

1. Load card, both sides.
2. Enter year, MM.DDYYYY.
3. Press A.
4. Display shows number of the day of year entered.
5. For a new date, go to step #2.

## Example-

11/26/82, 330

12/25/82, 359

001 f LBL A	31 25 11	049 3	03	097 GTO 1	22 01
002 DSP 6	23 06	050 g X>Y?	32 81	098 1	01
003 f -x-	31 84	051 GTO 2	22 02	099 0	00
004 f X<0?	31 71	052 RCL 3	34 03	100 STO-7	33 51 07
005 h SF 0	35 51 00	053 h F? 0	35 71 00	101 GTO 1	22 01
006 h ABS	35 64	054 GTO B	22 12	102 f LBL 4	31 25 04
007 ENTER	41	055 1	01	103 4	04
008 f INT	31 83	056 5	05	104 ÷	81
009 STO 1	33 01	057 8	08	105 g FRAC	32 83
010 h R ↓	35 53	058 2	02	106 f X=0?	31 51
011 g FRAC	32 83	059 h X↔Y	35 52	107 GTO E	22 15
012 EEX	43	060 g X>Y?	32 81	108 GTO 1	22 01
013 2	02	061 GTO C	22 13	109 f LBL E	31 25 15
014 x	71	062 g X≠Y?	32 51	110 1	01
015 ENTER	41	063 GTO D	22 14	111 STO-7	33 51 07
016 f INT	31 83	064 GTO 4	22 04	112 GTO 2	22 02
017 STO 2	33 02	065 f LBL B	31 25 12	113 f LBL 1	31 25 01
018 h R ↓	35 53	066 RCL 3	34 03	114 2	02
019 g FRAC	32 83	067 1	01	115 STO-7	33 51 07
020 EEX	43	068 -	51	116 f LBL 2	31 25 02
021 4	04	069 GTO 4	22 04	117 RCL 7	34 07
022 x	71	070 f LBL C	31 25 13	118 DSP 0	23 00
023 STO 3	33 03	071 RCL 3	34 03	119 f -x-	31 84
024 1	01	072 EEX	43	120 h CF 0	35 61 00
025 2	02	073 2	02	121 f CL REG	31 43
026 RCL 1	34 01	074 ÷	81	122 h RTN	35 22
027 g X>Y?	32 81	075 STO 9	33 09		
028 GTO f e	22 31 15	076 g FRAC	32 83		
029 2	02	077 f X≠0?	31 61		
030 7	07	078 GTO 3	22 03		
031 5	05	079 RCL 9	34 09		
032 x	71	080 f INT	31 83		
033 9	09	081 GTO 4	22 04		
034 ÷	81	082 f LBL 3	31 25 03		
035 f INT	31 83	083 RCL 3	34 03		
036 3	03	084 GTO 4	22 04		
037 0	00	085 f LBL D	31 25 14		
038 -	51	086 1	01		
039 RCL 2	34 02	087 0	00		
040 +	61	088 0	00		
041 STO 7	33 07	089 4	04		
042 h LST X	35 82	090 RCL 1	34 01		
043 3	03	091 EEX	43		
044 1	01	092 2	02		
045 h X↔Y	35 52	093 x	71		
046 g X>Y?	32 81	094 RCL 2	34 02		
047 GTO f e	22 31 15	095 +	61		
048 RCL 1	34 01	096 g X≤Y?	32 71		