

STEP KEY ENTRY KEY CODE

1	LBL E	31 25 15
	FP 0	35 71 00
	GTO 3	22 03
	RCL 0	34 00
5	X = 0	31 51
	GTO 0	22 00
	GSB 2	31 22 02
	RCL E	34 15
	X	71
10	STO 6	33 06
	STO 9	33 09
	GSB 2	31 22 02
	RCL 4	34 04
	X	71
15	STO 7	33 07
	STO + 9	33 61 09
	GSB 2	31 22 02
	STO 8	33 08
	STO + 9	33 61 09
20	1	01
	STO - 0	33 51 00
	RCL 9	34 09
	DSP 0	23 00
	RTN	35 22
25	LBL A	31 25 11
	SF 0	35 51 00
	SF 1	35 51 01
	RTN	35 22
	LBL B	31 25 12
30	SF 0	35 51 00
	SF 2	35 51 02
	RTN	35 22
	LBL C	31 25 13
	SF 0	35 51 00
35	SF 3	35 51 03
	RTN	35 22
	LBL c	32 25 13
	SF 0	35 51 00
	SF 1	35 51 01
40	SF 2	35 51 02
	SF 3	35 51 03
	RTN	35 22
	LBL 0	31 25 00
	DSP 9	23 09
45	RTN	35 22
	LBL 2	31 25 02
	GSB 1	31 22 01
	X = 0	31 51
49	GTO (1)	22 24
50	RTN	35 22
	LBL 1	31 25 01
	RCL 1	34 01
	DI	35 73
	X	32 54
55	X	71
	PRAC	32 83
	STO 1	33 01
	RCL 4	34 04
	X	71
60	INT	31 83
	RTN	35 22
	LBL 3	31 25 03
	CF 0	35 61 00
	FP 1	35 71 01
65	GTO 4	22 04
	GSB 2	31 22 02
	RCL E	34 15
	STO 9	33 09
	LBL 5	31 25 05
70	FP 2	35 71 02
	GTO 6	22 06
	GSB 2	31 22 02
	RCL 4	34 04
	X	71
75	STO + 9	33 61 09
	LBL 7	31 25 07
	FP 3	35 71 03
	GTO 8	22 08
	GSB 2	31 22 02
80	GTO 9	22 09
	LBL 4	31 25 04
	CF 1	35 61 01
	RCL 6	34 06
	STO 9	33 09
85	GTO 5	22 05
	LBL 6	31 25 06
	RCL 7	34 07
	STO + 9	33 61 09
	GTO 7	22 07
90	LBL 8	31 25 08
	RCL 8	34 08
	LBL 9	31 25 09
	STO + 9	33 61 09
	RCL 9	34 09
95	PAUSE	35 72
	RCL E	34 15
	/	81
	PRAC	32 83
100	RCL B	34 12

STEP KEY ENTRY KEY CODE

1	PRAC	32 83
	X # 0	31 61
	GTO a	22 31 11
	LST X	35 82
5	STO + 0	33 61 00
	RCL 9	34 09
	RCL C	34 13
	/	81
	PRAC	32 83
10	X # 0	31 61
	GTO a	22 31 11
	LST X	35 82
	STO + 0	33 61 00
	LBL a	32 25 11
15	RCL 9	34 09
	RCL D	34 14
	/	81
	PRAC	32 83
	X # 0	31 61
20	GTO a	22 31 11
	LST X	35 82
	4	04
	x	71
	STO + 0	33 61 00
25	LBL a	32 25 11
	RCL 0	34 00
	CHS	42
	RTN	35 22
	LBL b	32 25 12
30	CF 0	35 61 00
	CF 1	35 61 01
	CF 2	35 61 02
	CF 3	35 61 03
	RTN	35 22
35	LBL D	31 25 14
	STO - 2	33 51 02
	.	83
	2	02
	5	05
40	/	81
	INT	31 83
	STO + 0	33 61 00
	RCL 0	34 00
	CHS	42
45	DSP 0	23 00
	CF 3	35 61 03
	RTN	35 22
	LBL d	32 25 14
49	RCL 0	34 00
50	.	83
	2	02
	5	05
55	X	71
	RCL 2	34 02
	+	61
	DSP 2	23 02
	RTN	35 22
	LBL e	32 25 15
	CL REG	31 43
60	STO 1	33 01
	1	01
	0	00
	ENTER	41
	X2	32 54
65	STO E	33 15
	X : Y	35 52
	STO 4	33 04
	X	71
	STO A	33 11
70	2	02
	CHS	42
	ST I	35 33
	.	83
	1	01
75	1	01
	STO B	33 12
	1	01
	1	01
	1	01
80	STO C	33 13
	1	01
	2	02
	3	03
	STO D	33 14
85	GSB b	32 22 12
	CL X	44
	RTN	35 22
90		
95		
100		

1. The "One-Armed Bandit" BY: Roelf Backus (1782),

2. BY: The Netherlands

1 Cancel all All hold. Pay back. Seed/Start holds.

HOLD I HOLD II HOLD III PAY PULL

67

2

STEP	INSTRUCTIONS	INPUT DATA/UNITS	KEYS	OUTPUT DATA/UNITS
1	Enter "seed" (0.3547....)	u	f e	0.
2	Enter your payment. (say 2.50)	2.50	D	-10.
	-10. is the number of games.			
3	"Pull" the handle.		E	n
	n is a random three digit number.			
4	You can (but you don't have to) now try to form a winning combination by holding one, two or three digits, and pull the handle again.		A/B/C	(new-n)
	See during pause the new combination.		E	
	After that, see the new amount of games.			
5	GTO step 3.			
6	If you see: 0.000000000, Enter payment again GTO step 2.			
7	To see the money you've earned (if pos.)		f d	
8	f b cancels all hold keys, GTO step 3 or 4.			
9	For a new game, or another player GTO step 1.			

STEP	KEY ENTRY	KEY CODE
201		
205		
210		
215		
220		
224		

Winning Combinations:				
x11 pays 1	111 pays 2	123 pays 4		
x22 pays 2	222 pays 4	246 pays 8		
x33 pays 3	333 pays 6	369 pays 12		
x44 pays 4	444 pays 8	492 pays 16		
etc.	etc.	615 pays 20		
		738 pays 24		
		861 pays 28		
		984 pays 32		
Comments:				
Winning points are always collected after one or more HOLD keys are used. So if you pull the handle and get in one time 492, you have to press f c (All Hold) and E to collect your 16 points!				

STEP KEY ENTRY KEY CODE

201		
205		
210		
215		
220		
224		

Registers

0 games	1 seed	2 pay	3	4 10
5	6 I	7 II	8 III	9 I, II, III

0	1	2	3	4
5	6	7	8	9

A 1000	B .11	C 111	D 123	E 100	F -2
All Labels used					

A	B	C	D	E
a	b	c	d	e
0	1	2	3	4
5	6	7	8	9

Flag Set Status

0 off	1 off	2 off	3 off
-------	-------	-------	-------

DSP 0.

V4 N9

PAGE 13

HP-65
USERS
CLUB