

HP-41C XROM Number Generator by Richard Nelson  
PPC Calculator Journal V7 N2 P31 Feb-Mar 1980

```
01 LBL "XROM" ;XROM Number Generator
02 STO 00
03 64
04 MOD
05 STO 01
06 X<>Y
07 144
08 -
09 4
10 *
11 RCL 00
12 64
13 /
14 INT
15 +
16 "XROM "
17 FIX 0
18 CF 29
19 64
20 MOD
21 XEQ 00
22 ARCL X
23 >"," ;Append comma
24 RCL 01
25 XEQ 00
26 ARCL X
27 AVIEW
28 STOP
29 LBL 00
30 9
31 X<>Y
32 X<=Y?
33 >"0" ;Append zero
34 RTN
35 END
```

0042C000F50058524F4D3016144B3171111414411442201614  
436840F558524F4D209C00A91D16144BE000009B73F27F2C21  
E000009B737E8401197146F27F3085C0000D1B

66 BYTES

# HP-41C XROM # Generator by Richard Nelson PPC V7 N2 P31 Feb-Mar 1980

Program Registers Needed: 10

Row 1 (1 - 5)



Row 2 (6 - 15)



Row 3 (16 - 20)



Row 4 (21 - 26)



Row 5 (26 - 35)



Row 6 ( 35 )

